1) Go into your computer's Settings.



2) Click Devices.



3) Click on Printers & Scanners.



4) Add the printer if it's not there then click the Zebra printer.

÷	Settings			
ŝ	Home		Printers & scanners	
Find a setting ρ			Add printers & scanners	
Devices			+ Add a printer or scanner	
	Bluetooth & other devices			
ß	Printers & scanners		Printers & scanners	
Ū	D Mouse		ZDesigner GK420d	
	Touchpad	- If ZDesigner or Lab need to install the	bel does not show, then add the printer (you'll e driver from the zebra.com website).	
	Typing	- Then click the ZDesigner printer (or Label printer if it's been		
D	Pen & Windows Ink	renamed)		
(\mathbb{A})	AutoPlay			
Ö	USB			





6) Open the Printer Properties window.



7) Change the printer's name to be Label.

🖶 ZDesigner	GK420d Prope	erties			×
Printer Setting	s Stocks La	inguage	Barcode F	onts Comman	nd Fonts About
General	Sharing Port	s Adva	anced	Color Managem	ent Security
5	Label	Chan	ge nam	e to Label	
Location:					
Comment:					
Model	7Designer (SK420d			
Model: ZDesigner GK420d					
Color: No Paper available:					
Double-s	Double-sided: No Staple: Unknown		User defined		
Staple: Ur					
Speed: Unknown					
Maximum resolution: 203 dpi				\sim	
	_				
		Pr <u>e</u> fer	ences	Print 1	est Page
	OK	Can	cel	Apply	Help

8) Go to the Stocks tab and setup the 4x8 stock.

rinter Settings Stocks Language Barcode Fonts Comma Defined stocks	and Fonts About	
Click the Stocks tab	Define Stock Name 4x8	? ×
	Options Darkness Speed	Enter 4x8 for the Name
Stock description	Dimensions Label Width Label Height	Enter Width of 4 4.00 and Height of 8 8.00 inch
Description	Unprintable Area	
Define your own label stock here and save it for future us stores label dimensions and some printer settings.	Left 0.0 Right 0.0 Click OK	0 Top: 0.00 10 Bottom: 0.00
Click New	ок	Cancel Help
New Change	Delete	

9) Set layout for the	ZDesigner GK420d Properties				
Preferences window.	Printer Settings Stocks Language Barcode Fonts Command Fonts About General Sharing Ports Advanced Color Management Security				
	Seneral tab				
	ZDesigner GK420d Printing Preferences				
	Command Fonts Custom Commandes Import/Export settings Tools About Location: Options Advanced Setup Dithering Stocks Printer Memory Barcode Fonts				
	Comment: No. Of Copies: Speed: 5 - "/-				
	Darkness: 15 Stocks: 4x8				
	Model: ZDesigner GK420d Paper Format Features C cm C portrait				
	Color: No Paper available: Omm Caladscape				
	Staple: Unknown User defined Size				
	Speed: Unknown Width: 4.00 Check rotate 18				
	Click Preferences 203 dpi				
	Preferences Print Left 0.00 Top: 0.00 Right 0.00 Bottom: 0.00				
	OK Cancel Apply				
	Click OK				
	K Cancel Apply Help				
10) Set layout for Printing Defaults.	Printer Settings Stocks Language Barcode Fonts Command Fonts About General Sharing Ports Advanced Color Management Security				
	Always available Advanced tab				
	O Available from 12:00 AM ↔ To 12:00 AM ↔				
	Priority: 1 Image: Constraint of the second secon				
	Driver: ZDesigner GK420d Command Fonts Custom Commands Import/Export settings Tools About Options Advanced Setup Dithering Stocks Printer Memory Barcode Fonts				
	Spool print documents so program finish No. Of Copies:				
	O Start printing after last page is spoole Speed: 5 "/s				
	Start printing immediately Darkness:				
	O Print directly to the printer				
	Hold mismatched documents				
	Print spooled documents first				
	Keen printed documents				
	Click Printeing Defaults Figure auvanceu printing reatures Width: 4.00				
	Printing Defaults Print Processor Height 8.00 Unprintable Area				
	OK Cancel Left 0.00 Top: 0.00 Right 0.00 Bottom: 0.00				
	Click OK				
	OK Cancel Apply Help				

11) Print Test Page.

E ZDesigner GK420d Properties X					
Printer Settings Stocks Languag General Sharing Ports	ge Barcode Fonts Command Fonts About Advanced Color Management Security				
S Label					
General Tab					
Location:					
Comment:					
Model: ZDesigner GK420	d				
Features					
Color: No	Paper available:				
Double-sided: No	4x8 ^				
Staple: Unknown	User defined				
Speed: Unknown	Click Print Test Page				
Maximum resolution: 203 dpi					
P	references Print Test Page				
ОК	Cancel Apply Help				

12) Your test print should look something like this.

